

(19)



Europäisches Patentamt
European Patent Office
Office européen des brevets



(11)

EP 0 464 908 B1

(12)

EUROPEAN PATENT SPECIFICATION

(45) Date of publication and mention
of the grant of the patent:
04.09.1996 Bulletin 1996/36

(51) Int Cl.⁶: **G06K 11/16, G06F 3/033**

(21) Application number: **91201581.5**

(22) Date of filing: **20.06.1991**

(54) Touch sensor array systems and display systems

System einer Berührungsmessfühlergruppe und Anzeigesystem

Système avec groupe de palpeurs à touches et système d'affichage

(84) Designated Contracting States:
DE FR GB

(30) Priority: **29.06.1990 GB 9014529**

(43) Date of publication of application:
08.01.1992 Bulletin 1992/02

(73) Proprietors:
• **PHILIPS ELECTRONICS UK LIMITED**
Croydon CR9 3QR (GB)
Designated Contracting States:
GB
• **Philips Electronics N.V.**
5621 BA Eindhoven (NL)
Designated Contracting States:
DE FR

(72) Inventor: **Edwards, Martin John**
Surrey RH1 5HA (GB)

(74) Representative: **Williamson, Paul Lewis et al**
Philips Electronics UK Limited
Patents and Trade Marks Department
Cross Oak Lane
Redhill, Surrey RH1 5HA (GB)

(56) References cited:
US-A- 4 145 748 **US-A- 4 520 357**
US-A- 4 839 634

Note: Within nine months from the publication of the mention of the grant of the European patent, any person may give notice to the European Patent Office of opposition to the European patent granted. Notice of opposition shall be filed in a written reasoned statement. It shall not be deemed to have been filed until the opposition fee has been paid. (Art. 99(1) European Patent Convention).

EP 0 464 908 B1

Description

This invention relates to a touch sensor array system including an array of sensing elements arranged according to rows and columns and provided with addressing means on the basis of row and column conductors for selectively addressing a particular one of said sensing means at an intersection of a selected row conductor and a selected column conductor in accordance with the preamble of claim 1. Such a system is known from US-A-4 839 634. In general, these kinds of systems may be used as an overlay for the display screen of an liquid crystal or other display device to provide for example selected inputs to the device in accordance with touched positions in the sensor array. In another example, the system may be used as a stand-alone graphics tablet connected to a computer system.

Various other kinds of touch sensor array systems are known.

In a particular kind of touch sensor array system, capacitive effects are utilised. In an example, pairs of spaced conductive strips or pads are provided which can either be physically displaced with respect to one another in response to finger pressure so as to alter the capacitance therebetween or capacitively coupled together in response to proximity of a user's finger.

Such systems typically have only limited resolution capabilities.

Inter alia, it is an object of the present invention to provide an improved touch sensor array system, which offers the capability of high resolution.

According to one aspect of the present invention, each sensing element comprises a bistable circuit at the sensing element's location in the array, which bistable circuit is responsive to a presence or absence of a touch input at the location of the sensing element so as to adopt a first or a second stable state respectively that remains continuously addressable, and which upon addressing by addressing means provides an output in accordance with its actual state, said system having reset means for periodically resetting the bistable circuits of the sensing elements.

Touching of the sensing elements for example may be by means of a user's finger or by means of a stylus. Upon touching by such position designating objects the bistable circuit is caused to adopt a certain stable state which is different to the stable state adopted by the circuit in the absence of a touch input so that a clear, unambiguous indication of touching is obtained. Following the adoption of one or other state, the bistable circuit remains in that state until it is next called upon to sense touching and therefore acts in the manner of a memory element whose state is determined by touching, and which, by interrogation, can provide an indication of touching after the event, enabling the touched locations in the array to be ascertained. The addressing means, by periodically resetting the bistable circuits, and preferably at regular intervals, enables a series of succes-

sive touches, or absence of touches, to be detected.

Preferably, the sensing elements each include a respective switching device in a matrix of switching devices and are actively addressable through operation of the switching devices by the addressing means to connect the bistable circuits to a state detection circuit of the addressing means. Such active addressing of the sensing elements enables large numbers of sensing elements to be used in the array thereby providing a high element density or high resolution and without the kind of problems which could be expected when using a simple multiplexing technique for monitoring the sensing element states. The active addressing of the sensing elements, and hence the monitoring of their states, desirably is carried out at intervals related to the periodic resetting of the bistable circuits by the addressing means.

In a preferred embodiment the active matrix switching devices comprise transistors. Although other forms of switching devices such as two-terminal non-linear devices, e.g. diodes or MIMs, could be used it is felt that transistors provide the simpler approach for actively addressing the sensing elements.

Preferably, the bistable circuit of each sensing element is responsive to a capacitive effect produced by position designating means, e.g. a finger or stylus, in proximity to the sensing element. Each sensing element may include a sensing electrode which, in conjunction with the touch designating means adjacent thereto, provides a certain, characteristic, capacitance. The bistable circuit responds to the existence of this capacitance to adopt its first state. This can be achieved conveniently in practice using a bistable circuit comprising two cross-coupled inverters with the sensing electrode being connected to a respective one of the bistable nodes and a reference capacitance being connected to the other bistable node. If the two capacitances are not the same then an imbalance in voltages present at the nodes will exist and following resetting of the bistable circuit to a metastable state the bistable circuit adopts a state depending on which of the capacitances is greater. A layer of insulating material may conveniently be provided over the sensing electrodes of the sensing elements. The electrode and the position designating means either on, or in close proximity to, the exposed surface of the insulating layer constitute respective capacitor plates with the insulating layer serving as the capacitor dielectric. The physical dimensions of the electrode and overlying insulating layer are selected such that the value of the capacitance obtained upon the position designating means being presented in relation to the value of the reference capacitance causes the bistable circuit to switch appropriately. With this sensing electrode arrangement no direct external connection to the sensing electrode is required. The insulating layer can conveniently be of hard wearing material so that even with extensive use of a stylus damage does not occur to the sensing elements. The insulating layers of the sensing elements can comprise respective portions of a com-

mon layer extending continuously over the array of sensing elements. Consequently a continuous and protective sensing surface is provided.

Each bistable circuit comprising cross-coupled inverters may further include a switching transistor connected across the inputs of the two inverters and which is operable by the addressing means to set the bistable circuit in its metastable state.

Other types of bistable circuits could be used if desired. Also, it is considered that the sensing elements can be responsive to a touch input other than by using a capacitive approach. However, the latter is advantageous in that it avoids the need for direct electrical connections and allows the use of an insulating covering layer to provide a rugged sensing surface.

The bistable circuits of the sensing elements preferably comprise thin film transistors (TFTs). Similarly the active matrix transistors may also comprise TFTs. The processing of TFTs, particularly amorphous or polycrystalline silicon TFTs, on large area glass substrates is already well developed for active matrix liquid crystals display devices. Both the array of sensing elements and the active matrix switches can be fabricated using this technology. The sensor array shares many similarities with active matrix display devices, and fabrication of the sensor array by thin film deposition and patterning techniques used in active matrix switching technology is therefore particularly convenient. The additional components, such as addressing and monitoring conductors, capacitor elements, and insulated electrodes, are analogous to components often present in active matrix display devices, where picture elements comprise element electrodes, possibly with associated storage capacitors, connected via switching TFTs to row and column address conductors.

Using this technology, the sensor array can be fabricated with individual sensing elements of comparable size to picture elements in display devices. This has important implications in that high resolution is readily achievable.

According to another aspect of the present invention, there is provided a display system comprising a display device and a touch sensor array system according to the one aspect of the invention in which the sensing elements of the array are positioned over the display output of the display device. The display could, for example, be a liquid crystal display device comprising a matrix array of individually controllable pixels. The sensor system according to the invention offers an important advantage over known system when used with display devices, particularly of the aforementioned kind, in that a 1:1 pixel to sensing element relationship is obtainable especially, for example, when TFT active matrix technology is employed in the fabrication of the sensor array.

Various embodiments of touch sensor array systems in accordance with the present invention will now be described, by way of example, with reference to the

accompanying drawings, in which:-

Figure 1 is a simplified schematic diagram of one embodiment of touch sensor array system in accordance with the invention showing an array of individual sensing elements together with associated circuits;

Figure 2 shows schematically the equivalent circuit of a typical sensing element of the array;

Figure 3 illustrates a particular implementation of the sensing element;

Figure 4 illustrates typical waveforms in operation of the sensing elements;

Figure 5 illustrates the circuit of a part of the sensor array comprising one complete sensing element and associated active matrix switching device;

Figure 6 illustrates typical waveforms present in the operation of the circuit part shown in Figure 5;

Figure 7 shows schematically part of a detection circuit of the system; and

Figures 8 and 9 illustrate respectively the circuit of a part of an alternative embodiment of sensor array device showing a typical sensing element together with its associated active matrix switching device, and typical waveforms appearing in operation of this embodiment.

The Figures are merely schematic and are not drawn to scale. In particular certain dimensions may have been exaggerated whilst others may have been reduced. The same reference numerals are used throughout to denote the same or similar parts.

Referring to Figure 1, the touch sensor system includes an array of sensing elements carried on a common substrate to form a sensing panel 10.

Each sensing element, referenced at 12, comprises a bistable circuit 14 connected to an insulated sensing electrode 15 which constitutes one side of a capacitor, the other side being the touching object, either a grounded stylus or, for example, a finger of a user. The state of the bistable circuits is dependent on touching. If the sensing electrode of a particular sensing element is touched the associated bistable circuit adopts a certain indicative state. The sensing elements are combined in an active matrix comprising switching devices 16, each sensing element including a respective switching device, with row and column addressing conductors to allow the state of each row of sensing elements to be read and the positions that have been touched to be determined.

The sensing elements 12 are in an X-Y array consisting of r rows (1 to r) with c elements (1 to c) in each row. Only a few sensing elements are illustrated in Figure 1 for simplicity. In practice there may be a several hundred columns and rows, the numbers chosen depending on the intended use. If used, for example, as a user interface for a computer graphics system, the number of sensing elements and the ratio of rows to col-

umns would be dependent on the pixel count and aspect ratio of the system's display. If used as a display overlay, a 1:1 correspondence between pixels and sensing elements could be provided.

The circuit configuration of part of a typical sensing element 12 is shown in Figure 2. The element consists of a bistable circuit 14 comprising two cross-coupled inverters 17 and 18 and a switching transistor 19 connected between the two inverter inputs and whose control (gate) electrode is connected to a line 20 along which regular clocking, selection, signals are provided. One of the bistable nodes, referenced B, is connected to a sensing electrode 15, in the form of a rectangular pad of conductive material which is covered by an insulating layer, constituting the sensing element's input. The other node of the bistable circuit, referenced A, is connected to a reference capacitor 21 and also acts as the sensing element output, the output being provided along line 22.

An example implementation of this circuit configuration using NMOS transistors is illustrated in Figure 3. Two transistors 25, 26 connected in series are arranged in parallel with two other series-connected transistors 27 and 28 between positive and negative rails 23 and 24 with the gates of transistors 25 and 28 also being connected to the rail 23. The sensing electrode 15 is connected to the gate of transistor 27 as well as node B whereas node A is connected to one side of the reference capacitor 21 which is also connected to the gate of transistor 26, the other side of the capacitor 21 being connected to the rail 24. The power supply rails 23 and 24 are shared by the bistable circuits of all other sensing elements in the same row, other rows of sensing elements being similarly associated with respective pairs of supply rails as shown in Figure 1.

The bistable circuit 12 has two stable states, a first where A is high and B is low and a second where A is low and B is high, and a third state which is a metastable state where A and B are equal. When in this latter condition the bistable circuit is very sensitive to any imbalance introduced in the voltages at A and B and will readily revert to either the first or the second state depending on the sense of the imbalance.

In operation of the sensing element, the bistable circuit 12 is first set to its metastable state by taking the clock signal, Ck, on line 20 high to turn on the transistor 19. When turned on the transistor 19 connects nodes A and B and the voltages at these two nodes equalise at a voltage lying between the high and low logic levels. When the clocking signal Ck thereafter returns to a low level the negative going edge of the signal is coupled through onto nodes A and B by the parasitic gate/source and gate/drain capacitances Cs of transistor 19. These capacitances Cs, which are substantially equal, are shown in dotted outline in Figure 2. The capacitances Cs could instead be provided by two discrete capacitors. The magnitude of the voltage shift at nodes A and B caused by the presence of the respective capacitances

Cs will depend on the value of the additional capacitance present at the associated node which for node A is the capacitance, Cr, of the reference capacitor 21 and for node B is the capacitance, Ce, of the input sensing electrode 15. If these capacitances are not the same then an imbalance in the circuit voltages is produced and since the nodes A and B are no longer interconnected by the transistor 19 the bistable circuit will flip into one or other of its two stable states depending on the relative values of the two capacitances. For example if the sensing electrode capacitance Ce is less than the reference capacitance Cr then the coupling of the signal Ck will cause the voltage at node A to be higher than that at node B and consequently the bistable circuit will flip into the state with A high and B low. Conversely, if the sensing electrode capacitance Ce is greater than the reference capacitance Cr the resulting voltage at node B will be greater than that at node A and the bistable circuit will switch to the opposite state in which node A is low and node B is high. The capacitance Ce of sensing electrode 15 can be of two distinct values according to whether or not a touch input is made to the sensing element, i.e. a higher capacitance is exhibited when a grounded finger or stylus is placed on, or closely adjacent, the surface of the dielectric layer covering the electrode 15. By selecting the value of Cr appropriately in relation to the capacitance at electrode 15 obtained by a touch input, which itself is dependent on the physical dimensions of the electrode 15 and the thickness of the insulating layer, the bistable circuit detects and responds to the increase in capacitance of the electrode 15 caused by touching the electrode with a finger or grounded stylus. Representative waveforms in operation of the sensing element are shown in Figure 4, in which Ck is the clocking pulse signal waveform applied to the transistor 19, and V_A and V_B are, respectively, the voltages appearing at nodes A and B. Figure 4a illustrates the case where Ce is less than Cr, i.e., for no touch input, and Figure 4b illustrates the case where Ce is greater than Cr, i.e., for a touch input.

The array of sensing elements 12 of the sensing panel 10 are combined with the active matrix switching devices 16 together with driving and addressing conductors in the manner depicted, by way of illustration, in Figure 5, which shows the circuit configuration of one complete, and representative, sensing element in the Nth row of Mth column of the array. The X-Y array of sensing elements 12 is driven and addressed via sets of row and column conductors with the sensing elements being located adjacent respective intersections of the column and row conductors. The clocking signals Ck for the transistor 19 (and the transistors 19 of other elements in the same row) are applied along a row conductor, 20, shared by all sensing elements 12 of the row. Similarly, the positive and negative (ground) supply lines 23 and 24 extend as row conductors and are shared by all other sensing elements in the same row. Referring also again to Figure 1, the row conductors 23 and 24

are connected at their ends adjacent the periphery of the panel respectively to supply rails 31 and 32 to which the outputs of a power supply circuit 33 are coupled. Each column of sensing elements is associated with a respective one of a set of column, detection, conductors 34 to which the active matrix switching devices 16, comprising FET transistors, are connected. Referring to Figure 5 particularly, the switching device 16 associated with each sensing element consists of two switching transistors 36 and 37 connected in series between the associated column conductor 34 and the supply conductor 24 with their gates connected respectively to the clock signal row conductor 20 associated immediately with the succeeding, (N+1)th, row of sensing elements and the node A of the bistable circuit of the sensing element.

The ends of the row conductors 20 and column conductors 34 are connected respectively to a row address circuit 40 which produces the clocking signals, and a column detection circuit 41 (Figure 1) whose operations are controlled and synchronised by a timing and control circuit 43. The row addressing driver circuit 40 scans the conductors 20 sequentially with a clock pulse so that each complete row of sensing elements is reset and operated in turn, the clock pulses serving also to enable the states of the preceding row of sensing elements to be read out, and detected, via the column conductors 34, by the circuit 41 which provides an output at 58 indicative of the states of each row of sensing elements in turn. The first and last rows of the array differ slightly in that one of the two row conductors 20 associated with each of these rows is dedicated solely to that row (as shown in Figure 1) so that there are r+1 conductors 20 in all. Scanning of the set of row conductors 20 by the circuit 40 is repeated in regular fashion in successive field periods.

In the version of the system shown in Figure 1, a grounded stylus 50 is manipulated by a user to touch an appropriate sensing element, although it will be appreciated that the stylus can be replaced by a user's finger.

Figure 6 illustrates typical waveforms present in operation of the system of Figures 1 and 5 for a particular sensing element. Ck(N) and Ck(N+1) are the clocking pulse signals applied by the circuit 40 to the Nth and (N+1)th row conductors 20. Upon receipt of the clocking pulse Ck(N) the bistable circuit of the sensing element (and all other elements in the Nth row) is reset and then immediately thereafter switches to one or the other of its two possible stable states according to whether or not the sensing element is being touched. V_A and V_B represent, as before, voltage levels appearing at nodes A and B of the sensing element and in this particular example are indicative that the sensing element concerned is not being touched. The dotted lines signify the other possible state would be adopted in the event of a touch input.

When a clocking pulse, Ck, is applied to the next, (N+1)th, row conductor 20 to reset the bistable circuits

of the (N+1)th row of sensing elements, the active matrix switching device 16 of the sensing element (and all others in the Nth row) is operated to enable the state of the sensing element to be determined. The bistable output of the sensing element is connected to the gate of transistor 37 which, because the output (node A) is low in this example, is turned off. The Ck (N+1) clocking pulse turns on transistor 36 but connection between the column conductor 34 and supply (ground) conductor 24 is prevented because transistor 37 is off. On the other hand, if the bistable circuit was in its other stable state, with node A high indicating touching, transistor 37 is turned on and the series-connected transistors 36 and 37 then provide an interconnection between column conductor 34 and ground conductor 24.

The state of the bistable circuit of the sensing element is ascertained by detecting in the detection circuit 41 connected to the column conductor whether or not such an interconnection exists. This can be achieved in different ways. For example, the column conductor 34 can be pre-charged to a high voltage level before the (N+1)th row conductor 20 is addressed and then, upon switching of the matrix transistor 36 by the Ck (N+1)th clocking signal, detecting whether or not this voltage is discharged through operation of the transistor 37, depending on the state of the bistable circuit. The voltage waveform for the Mth column conductor for this mode of operation is shown at V_m in Figure 6, where t represents the precharging period and t1 the precharging period for the next row. Alternatively a current amplifier may be connected to the column conductor 34 to measure the current flow through the matrix transistors 36 and 37. The former technique allows logic level signals to be obtained directly from the column conductors of the matrix resulting in comparatively simple column drive circuitry. In this mode of operation the scanning rate of the rows of sensing elements may be limited as the active matrix transistors will require some time to discharge the capacitance of the column conductors. The latter technique requires a current or charge sensitive amplifier to be connected, in the detection circuit 41, to each column conductor 34 in order to convert the small signal from the active matrix transistors to the required logic levels.

By detecting the magnitude of the charging current with a respective sense amplifier connected to each column conductor, the system can determine which elements have been touched and their coordinates. Figure 7 illustrates part of one detection circuit suitable for such detection, the part shown comprising for simplification the circuit arrangement for just three consecutive columns of sensing elements. Each column conductor 34 of the panel 10 is connected to an input of an inverting amplifier 52 having a parallel feedback impedance 53. The detectors are rendered either charge or current sensitive by providing either a capacitive or a resistive feedback impedance 53. The outputs of the amplifiers 52 are fed to a signal processing circuit 54 comprising a parallel threshold circuit 55 responsive to the effect of large cur-

rent spikes in the column conductor waveform indicative of a sensing element associated with that column having been touched to provide appropriate digital signal outputs and a parallel latching circuit 56 connected to the outputs of the threshold circuit which latches the digital signals into a series of flip flops forming a shift register 57 to give a serial output 58.

By associating the output of the processing circuit 54 with operation of the row conductor driver circuit 40 unique signals identifying the coordinates of sensing elements which have been touched can be generated in ways known per se in touch sensor systems.

Each row of sensing elements is addressed by the addressing circuit 40 in turn, so that, after one complete field, an indication, or picture, of all sensing elements which have been touched and their position is obtained. Addressing of the array of sensing elements in this fashion is carried out in a recurrent cycle with the condition of each sensing element being repeatedly monitored in subsequent field periods. The duration of each field period may be varied as desired taking into account the number of rows of sensing elements in the array, the duration of the clocking pulses applied by the drive circuit 40, and the manner of operation of the detection circuit 41. Obviously the field period is chosen to be sufficiently small to ensure that relatively brief touch inputs are sensed. By way of example each field period may be approximately 20msec., thus giving a very rapid response to user inputs and detection of rapidly changing touch inputs.

In the above described embodiment, a conducting stylus coupled to ground potential is used as a tool for entering input information. This enables small area sensing elements to be used and, in turn, allows a high resolution array to be achieved which is beneficial for use as an interface for a graphics display system for example.

The circuit configuration of another embodiment of touch sensor panel is illustrated in part in Figure 8, similar in respects to Figure 5, and showing the circuit of a typical sensing element together with its associated driving and address conductors and active matrix switching transistors. In this embodiment, the need for a separate ground supply conductor to each row is avoided, use being made instead of the fact that the row conductors 20 are at ground potential except when a clocking pulse is actually being applied therealong. Typical waveforms present in operation of this embodiment are shown in Figure 9 for comparison with those of Figure 6.

In this circuit arrangement, a positive supply line 23 is again provided for each row of sensing elements. However the ground supply lines 24 previously described are not used and instead each row of sensing elements is associated with three clocking signal row conductors 20, rather than two as previously. Comparing Figure 8 with Figure 5, it will be seen that a main electrode of the transistor 37 of the active matrix tran-

sistors, the side of the reference capacitor 21 remote from the node A and the interconnection between the transistors 26 and 27 of the bistable circuit are all connected via a line 60 to the (N-1)th row conductor 20.

5 Operation of the sensing element, and likewise all other sensing elements in the same row, is generally similar to that of the previous embodiment. A clocking signal pulse applied to the Nth row conductor 20 resets the bistable circuit and, upon termination of this pulse, the 10 bistable circuit adopts one of other of its two possible stable states according to whether or not a touching input is made to the sensing electrode 15. The necessary grounding of circuit components is achieved through the line 60. Figure 9 illustrates the clocking pulse sequence 15 for the three consecutive, (N-1), N, and (N+1) row conductors 20 from which it will be seen that for the duration of the clocking pulses applied to the Nth and (N+1)th row conductors 20 the (N-1)th row conductor is held at ground potential. The state of the bistable circuit is read 20 out, as previously, upon turning on of the active matrix transistor 36 by a clocking pulse applied to the (N+1)th row conductor 20. The elimination of the need to use ground supply conductors means that fewer sets of row conductors are required. However, it becomes necessary 25 to provide an additional row conductor for the first row of sensing elements if these elements are to be fully operational.

With regard to both embodiments, fabrication of the array of sensing elements, the active matrix, and the address and driving conductors is based on technology 30 used in active matrix addressed display devices, such as liquid crystal display devices. In active matrix display panels the picture elements each consist of a display element having first electrode carried on one substrate together with sets of row and column address conductors 35 and with one or more associated matrix switching transistors. (A second display element electrode is carried on a second, spaced, substrate with electro-optical, for example liquid crystal material, therebetween.) It will be appreciated, therefore, that there are many similarities 40 between the structure on the one substrate of these display panels and the above described touch sensing panels. Active matrix display device technology is now widely documented and well established as a means for producing large area active matrix arrays and as such 45 it is considered unnecessary to describe here in detail methods by which the panel of the sensing array system of the invention can be fabricated. Typically, this involves the deposition and patterning of a number of superimposed layers on a substrate. The active addressing of the sensing elements also is accomplished in 50 much the same fashion.

Although the sensing panel 10 is constructed in similar manner the processing is slightly more complex than 55 standard display panels because of the necessity to incorporate additional sets of conductors and seven transistors for each sensing element.

As in active matrix display devices, a glass sub-

strate is used with the transistors comprising thin film transistors (TFTs) using amorphous silicon or polycrystalline silicon technology. The address and driving conductors are formed by patterning metal layers, with appropriate insulation at cross-overs. The reference capacitors 21, and discrete supplementary capacitances Cs if required, are formed by defining metal pads from the deposited metal layers with insulative material therebetween. Similarly, the sensing electrode 15 is defined from a deposited opaque or transparent conductive layer, depending on how the system is to be used. The insulating layer covering the electrodes 15 is provided as a single layer extending over the whole area of the sensing element array to form a continuous sensing surface. The insulating layer serves also to provide a degree of electrical and mechanical protection for the sensing element array.

The physical dimensions of the sensing elements and particularly the sensing electrodes 15, may be varied to suit the particular requirements of the touch sensor array in use, for in accordance with the desired resolution characteristics. The sensing element dimensions may be of the same order as used for pixel elements in a display device, say around 100 micrometres square, or larger.

The above described embodiments of touch sensor systems may be used as a stand alone input interface. Alternatively they may be used as an overlay to a display device, for example a matrix liquid crystal display device or CRT. To this end, the sensing electrodes at least of the sensor elements should be transparent. The high resolution possible means that very precise position sensing can be achieved. When used as a display overlay, therefore, there can be a 1:1 relationship between the individual sensing elements and display pixels of the display device, for example an active matrix addressed liquid crystal display device. For a colour display one sensing element can be provided for each triplet of display elements. A typical liquid crystal display device comprises two spaced substrates carrying electrodes defining an array of pixels together with addressing conductors and with liquid crystal material therebetween. The sensing element array is mounted over the display device with each sensing element in registration with an individual display pixel.

It will be appreciated that various modifications to the described embodiments are possible. For example, the need for a dedicated reference capacitor 21 can be avoided by using instead parasitic capacitance of the TFT 37 as a reference capacitance. This parasitic capacitance can be increased by deliberately extending its gate contact over its source contact. Moreover, as will be understood by persons skilled in the art, alternative kinds of bistable circuit configurations, for example long tailed pair circuits, could be employed.

Although the described embodiments employ three-terminal transistor devices for the active addressing, it is envisaged that the sensing elements could be

actively addressed by means of two-terminal non-linear switching devices, such as diodes or MIMs for example, following technology already known and used in active matrix addressing of display devices.

Also, it is envisaged that the sensing elements could be made to be responsive to touch inputs other than by the capacitive approach utilised in the specific embodiments described, for example by using a technique which relies on direct electrical contact between the position designating means and a component of the sensing element so that the state adopted by the bistable circuit of a sensing element is determined by the presence or absence of such electrical contact.

From reading the present disclosure, other modifications will be apparent to persons skilled in the art. Such modifications may involve other features which are already known in the field of touch sensor array systems and which may be used instead of or in addition to features already described herein.

Claims

1. A touch sensor array system including an array of sensing elements (12) arranged according to rows and columns and provided with addressing means (40, 41) on the basis of row (20) and column (34) conductors for selectively addressing a particular one of said sensing elements at an intersection of a selected row conductor and a selected column conductor, characterised in that each sensing element (12) comprises a bistable circuit (14) at the sensing element's location in the array, which bistable circuit (14) is responsive to a presence or absence of a touch input at the location of the sensing element (12) so as to adopt a first or a second stable state respectively that remains continuously addressable, and which upon addressing by addressing means (40, 41) provides an output in accordance with its actual state, said system having reset means (19, 20, 40) for periodically resetting the bistable circuits (14) of the sensing elements (12).
2. A touch sensor array system according to Claim 1, characterised in that the sensing elements (12) each include a respective switching device (16) in an active matrix of switching devices and are actively addressable through operation of the switching devices (16) by the addressing means (40, 41) to enable a detection circuit (41) of the addressing means (40, 41) to detect the state of the bistable circuits (14).
3. A touch sensor array system according to Claim 2, characterised in that the addressing means (40, 41) actively addresses the sensing element (12) at intervals related to the periodic resetting of the bistable circuits (14).

4. A touch sensor array system according to Claim 2 or Claim 3, characterised in that the switching devices (16) comprise thin film transistors.
5. A touch sensor array system according to any one of Claims 2 to 4, characterised in that the sensing elements (12) are reset by the addressing means (40, 41) a row at a time in sequence.
6. A touch sensor array system according to Claim 5, characterised in that switching devices (16) of the sensing elements (12) are operated by the addressing means (40, 41) a row at a time in sequence.
7. A touch sensor array system according to Claim 6, characterised in that the sensing elements (12) are reset and the switching devices (16) are operated by selection signals (20) supplied via row address conductors (20) and in that the detection circuit (41) is connected to the switching devices via column detection conductors (34).
8. A touch sensor array system according to any one of Claims 1 to 7, characterised in that the bistable circuit (14) of each sensing element (12) is responsive to a capacitive effect produced by a position designating means in proximity to the sensing element (12).
9. A touch sensor array system according to Claim 8, characterised in that each sensing element includes a sensing electrode (15) which, in conjunction with the position designating means, provides a certain capacitance.
10. A touch sensor array system according to Claim 9, characterised in that the bistable circuit (14) of each sensing element (12) comprises two cross-coupled inverters (17, 18), in that the sensing electrode (15) is connected to a respective one (B) of the bistable nodes (A, B), and in that a reference capacitance (21) is connected to the other bistable node (A), the bistable circuit (14) being periodically reset by the addressing means (40, 41) to a metastable state following which resetting the bistable circuit adopts its first or second state depending on the relative values of the sensing electrode (15) and the reference capacitance (21).
11. A touch sensor array system according to Claim 10, characterised in that the bistable circuit (14) further includes a switching transistor (19) connected across the inputs of the two inverters (17, 18) which is operable by the addressing circuit (40, 41) to set the bistable circuit (14) to its metastable state.
12. A touch sensor array system according to any one of Claims 9 to 11, characterised in that a layer of

insulating material is provided over the sensing electrode (15) of each sensing element (12).

13. A touch sensor array system according to Claim 12, characterised in that the layers of insulating material comprise respective portions of a common and continuous layer of material extending over the array of sensing elements (12).
14. A touch sensor array system according to any one of Claims 10 to 13, characterised in that the bistable circuits comprise thin film transistors.
15. A touch sensor array system according to any of Claims 1 to 14 and comprising a display device having its display output area positioned in conjunction with the array so that the sensing elements are positioned over the display output.

Patentansprüche

1. System einer Berührungsmeßfühlergruppe, das eine Matrix aus Meßfühlern (12), die in Reihen und Spalten angeordnet sind, und Adressiermittel (40, 41) auf der Basis von Reihen- (20) und Spaltenleitungen (34) enthält, um ein bestimmtes der genannten Meßfühlermittel am Kreuzungspunkt einer ausgewählten Reihenleitung und einer ausgewählten Spaltenleitung zu adressieren, dadurch gekennzeichnet, daß jeder Meßfühler (12) eine bistabile Schaltung (14) an der Position innerhalb der Matrix umfaßt, in der sich der Meßfühler befindet, wobei die bistabile Schaltung (14) darauf reagiert, ob die genannte Position des Meßfühlers (12) berührt wird oder nicht, indem sie in einen ersten bzw. einen zweiten stabilen Zustand geht, der ständig adressiert werden kann, und die bei der Adressierung durch Adressiermittel (40, 41) ein Ausgangssignal in Übereinstimmung mit ihrem tatsächlichen Zustand liefert, wobei das genannte System Rückstellmittel (19, 20, 40) enthält, um die bistabilen Schaltungen (14) der Meßfühler (12) in regelmäßigen Abständen rückzustellen.
2. System einer Berührungsmeßfühlergruppe nach Anspruch 1, dadurch gekennzeichnet, daß jeder Meßfühler (12) jeweils ein Schaltelement (16) in einer aktiven Matrix von Schaltelementen enthält und aktiv adressiert werden kann, indem die Schaltelemente (16) durch die Adressiermittel (40, 41) so betätigt werden, daß eine Detektorschaltung (41) der Adressiermittel (40, 41) den Zustand der bistabilen Schaltungen (14) erfassen kann.
3. System einer Berührungsmeßfühlergruppe nach Anspruch 2, dadurch gekennzeichnet, daß die Adressiermittel (40, 41) die Meßfühler (12) in Ab-

ständen aktiv adressieren, die mit der regelmäßigen Rückstellung der bistabilen Schaltungen (14) in Beziehung stehen.

4. System einer Berührungsmeßfühlergruppe nach Anspruch 2 oder Anspruch 3, dadurch gekennzeichnet, daß die Schaltelemente (16) Dünnschicht-Transistoren enthalten.
5. System einer Berührungsmeßfühlergruppe nach einem der Ansprüche 2 bis 4, dadurch gekennzeichnet, daß eine Reihe mit Meßfühlern (12) nach der anderen durch die Adressiermittel (40, 41) rückgestellt wird.
6. System einer Berührungsmeßfühlergruppe nach Anspruch 5, dadurch gekennzeichnet, daß die Schaltelemente (16) einer Reihe mit Meßfühlern (12) nach der anderen von den Adressiermitteln (40, 41) aktiviert werden.
7. System einer Berührungsmeßfühlergruppe nach Anspruch 6, dadurch gekennzeichnet, daß die Meßfühler (12) rückgestellt und die Schaltelemente (16) aktiviert werden durch Auswahlssignale (20), die über die Reihenadressenleitungen (20) zugeführt werden, und daß die Detektorschaltung (41) mit den Schaltelementen über Spaltendetektorleitungen (34) verbunden ist.
8. System einer Berührungsmeßfühlergruppe nach einem der Ansprüche 1 bis 7, dadurch gekennzeichnet, daß die bistabile Schaltung (14) jedes Meßfühlers (12) auf eine von positionsbestimmenden Mitteln in der Nähe des Meßfühlers (12) erzeugte kapazitive Wirkung reagiert.
9. System einer Berührungsmeßfühlergruppe nach Anspruch 8, dadurch gekennzeichnet, daß jeder Meßfühler eine Fühlerlektrode (15) enthält, die zusammen mit den positionsbestimmenden Mitteln eine gewisse Kapazität erzeugt.
10. System einer Berührungsmeßfühlergruppe nach Anspruch 9, dadurch gekennzeichnet, daß die bistabile Schaltung (14) jedes Meßfühlers (12) zwei kreuzgekoppelte Inverter (17, 18) enthält, daß die Fühlerlektrode (15) mit einem entsprechenden (B) der bistabilen Knotenpunkte (A, B) verbunden ist und daß eine Referenzkapazität (21) mit dem anderen bistabilen Knotenpunkt (A) verbunden ist, wobei die bistabile Schaltung (14) regelmäßig von den Adressiermitteln (40, 41) in einen metastabilen Zustand rückgestellt wird, wonach die bistabile Schaltung in einen ersten oder zweiten Zustand geht in Abhängigkeit von den relativen Werten der Fühlerlektrode (15) und der Referenzkapazität (21).

11. System einer Berührungsmeßfühlergruppe nach Anspruch 10, dadurch gekennzeichnet, daß die bistabile Schaltung (14) außerdem einen Schalttransistor (19) enthält, der über die Eingänge der beiden Inverter (17, 18) angeschlossen ist und durch die Adressierschaltung (40, 41) so aktiviert wird, daß er die bistabile Schaltung (14) in ihren metastabilen Zustand bringt.

12. System einer Berührungsmeßfühlergruppe nach einem der Ansprüche 9 bis 11, dadurch gekennzeichnet, daß die Fühlerlektrode (15) jedes Meßfühlers (12) mit Isoliermaterial beschichtet ist.

13. System einer Berührungsmeßfühlergruppe nach Anspruch 12, dadurch gekennzeichnet, daß die Isolierschichten jeweils Anteile einer gemeinsamen durchgehenden Materialschicht enthalten, die sich über die Matrix der Meßfühler (12) erstreckt.

14. System einer Berührungsmeßfühlergruppe nach einem der Ansprüche 10 bis 13, dadurch gekennzeichnet, daß die bistabilen Schaltungen Dünnschicht-Transistoren enthalten.

15. System einer Berührungsmeßfühlergruppe nach einem der Ansprüche 1 bis 14, das ein Anzeigegerät enthält, dessen Anzeigeausgangsfläche so zusammen mit der Matrix angeordnet ist, daß sich die Meßfühler auf dem Anzeigeausgang befinden.

Revendications

1. Système à réseau de palpeurs à effleurement comprenant un réseau d'éléments de détection (12) agencés en rangées et en colonnes et pourvu de moyens d'adressage (40, 41) sur la base de conducteurs de rangées (20) et de colonnes (34) pour adresser sélectivement un élément particulier desdits éléments de détection à une intersection d'un conducteur de rangée sélectionné et d'un conducteur de colonne sélectionné, caractérisé en ce que chaque élément de détection (12) comprend un circuit bistable (14) à l'emplacement de l'élément de détection dans le réseau, ledit circuit bistable (14) étant sensible à la présence ou à l'absence d'une entrée d'effleurement à l'emplacement de l'élément de détection (12) de manière à adopter un premier ou un deuxième état stable, respectivement, qui reste adressable en permanence et qui, lors d'un adressage par les moyens d'adressage (40, 41), délivre une sortie en fonction de son état réel, ledit système comportant des moyens de remise à zéro (19, 20, 40) pour remettre à zéro périodiquement les circuits bistables (14) des éléments de détection (12).

2. Système à réseau de palpeurs à effleurement selon la revendication 1, caractérisé en ce que les éléments de détection (12) comprennent chacun un dispositif de commutation respectif (16) dans une matrice active de dispositifs de commutation et sont activement adressables par l'actionnement des dispositifs de commutation (16) par les moyens d'adressage (40, 41) pour permettre à un circuit de détection des moyens d'adressage (40, 41) de détecter l'état des circuits bistables (14). 5 10
3. Système à réseau de palpeurs à effleurement selon la revendication 2, caractérisé en ce que les moyens d'adressage (40, 41) adressent de manière active les éléments de détection (12) à des intervalles rapportés à la remise à zéro périodique des circuits bistables (14). 15
4. Système à réseau de palpeurs à effleurement selon la revendication 2 ou 3, caractérisé en ce que les dispositifs de commutation (16) comprennent des transistors à couches minces. 20
5. Système à réseau de palpeurs à effleurement selon l'une quelconque des revendications 2 à 4, caractérisé en ce que les éléments de détection (12) sont remis à zéro par les moyens d'adressage (40, 41) à raison d'une rangée à la fois en séquence. 25
6. Système à réseau de palpeurs à effleurement selon la revendication 5, caractérisé en ce que les dispositifs de commutation (16) des éléments de détection (12) sont activés par les moyens d'adressage (40, 41) à raison d'une rangée à la fois en séquence. 30 35
7. Système à réseau de palpeurs à effleurement selon la revendication 6, caractérisé en ce que les éléments de détection (12) sont remis à zéro et les dispositifs de commutation (16) sont activés par des signaux de sélection (20) délivrés via les conducteurs d'adressage de rangées (20) et en ce que le circuit de détection (41) est connecté aux dispositifs de commutation via des conducteurs de détection de colonnes (34). 40 45
8. Système à réseau de palpeurs à effleurement selon l'une quelconque des revendications 1 à 7, caractérisé en ce que le circuit bistable (14) de chaque élément de détection (12) est sensible à un effet capacitif produit par un moyen de désignation de position à proximité de l'élément de détection (12). 50
9. Système à réseau de palpeurs à effleurement selon la revendication 8, caractérisé en ce que chaque élément de détection comprend une électrode de détection (15) qui, conjointement avec le moyen de désignation de position, fournit une certaine capacité. 55
10. Système à réseau de palpeurs à effleurement selon la revendication 9, caractérisé en ce que le circuit bistable (14) de chaque élément de détection (12) comprend deux inverseurs à couplage croisé (17, 18), en ce que l'électrode de détection (15) est connectée à un noeud respectif (B) des noeuds bistables (A, B), et en ce qu'une capacité de référence (21) est connectée à l'autre noeud bistable (A), le circuit bistable (14) étant ramené périodiquement par les moyens d'adressage (40, 41) à un état métastable après quoi le circuit bistable adopte son premier ou son deuxième état en fonction des valeurs relatives de la capacité de l'électrode de détection (15) et de la capacité de référence (21).
11. Système à réseau de palpeurs à effleurement selon la revendication 10, caractérisé en ce que le circuit bistable (14) comprend par ailleurs un transistor de commutation (19) connecté aux bornes des entrées des deux inverseurs (17, 18), qui peut être activé par le circuit d'adressage (40, 41) pour amener le circuit bistable (14) à son état métastable.
12. Système à réseau de palpeurs à effleurement selon l'une quelconque des revendications 9 à 11, caractérisé en ce qu'une couche de matière isolante est appliquée sur l'électrode de détection (15) de chaque élément de détection (12).
13. Système à réseau de palpeurs à effleurement selon la revendication 12, caractérisé en ce que les couches de matière isolante comprennent des parties respectives d'une couche commune et continue de matière s'étendant sur le réseau d'éléments de détection (12).
14. Système à réseau de palpeurs à effleurement selon l'une quelconque des revendications 10 à 13, caractérisé en ce que les circuits bistables comprennent des transistors à couches minces.
15. Système à réseau de palpeurs à effleurement selon l'une quelconque des revendications 1 à 14 et comprenant un dispositif d'affichage dont la zone de sortie d'affichage est mise en place conjointement avec le réseau de telle manière que les éléments de détection soient placés sur la sortie d'affichage.

Fig.1.




Fig.2.




Fig.3.




Fig.4.




Fig.5.




Fig. 6.






Fig. 7.*Fig. 9.*

Fig.8.

